

DIMENSION

| Model | H1 | H2 | H3 | W1 | W2 | W3 | L1 | L2 | L3 |
|-------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|
| V260AH V260ASH | 425 | 205 | 145 | 130 | 165 | 175 | 175 | 210 | 265 |
| V460AH V460ASH | 430 | 205 | 145 | 130 | 165 | 175 | 175 | 210 | 265 |
| V760AH | 455 | 240 | 180 | 105 | 140 | 215 | 200 | 230 | 325 |



unit:(mm)

EXPLODED DRAWINGS



| | 3 7 ⁸ | 9 10 - | |
|------------|------------------|----------------------------|----|
| 2345 | NO. | Part Name | N |
| 23 | 0A | Protector Cover | |
| | 0B | Thermal overload protector | |
| (A)(B) | 1 | Front Cover | FC |
| | 2 | O-Ring | |
| | 3 | Screws | |
| _ | 4 | Washer | |
| III | _ | 1 11 | |



V260ASH.V460ASH Stainless Steel Pump

| NO. | Part Name | Material | |
|-----|----------------------------|---------------|---|
| 0A | Protector Cover | PP | |
| 0B | Thermal overload protector | | |
| 1 | Front Cover | FC20/SUS304 | |
| 2 | O-Ring | | |
| 3 | Screws | SUS304 | |
| 4 | Washer | SUS304 | |
| 5 | Impeller | Bronze | |
| 6 | Spring | SUS304 | |
| 7 | Bellowes | NBR | |
| 8 | Seat | SIC | |
| 9 | Cup | NBR | |
| 10 | Key | SUS304 | |
| 11 | Bronze liling | BC6 | |
| 12 | Pump Body | FC20/SUS304 | |
| 13 | Ring | Rubber | |
| 14 | Bearing(6201) | | |
| 15 | Bearing Board | SS41 | |
| 16 | Shaft | SUS420 | |
| 17 | Rotor | Silicon Steel | |
| 18 | Bearing(6201) | | |
| 19 | Bottom Base | ABS | |
| 20 | Gasket | NBR | ı |

| NO. | Part Name | Material |
|-----|-----------------------|---------------|
| 21 | Back Cover | FC20 |
| 22 | Fan | ABS |
| 23 | Fan Cover | ss41 |
| 24 | Motor Protector | |
| 25 | Label (Specification) | |
| 26 | Control Box | Nynon66 |
| 27 | Capacitor | |
| 28 | Stator | Silicon Steel |
| 29 | Stator Circuit | Copper |
| 30 | Pressure Switch | |
| 31 | Nozzle | SUS304 |
| 32 | Pressure Tank(3L) | PP |
| 33 | Diaphragm | CIIR |
| 34 | Outlet Flange | FC20/SUS304 |
| 35 | Gasket | NBR |
| 36 | Gasket | NBR |
| 37 | Inlet Flange | FC20/SUS304 |
| 38 | Gasket | NBR |
| 39 | Valve Nod | Nynon66 |
| 40 | Spring | SUS304 |
| 41 | Gasket | NBR |
| 42 | Covering | PP |






AUTO BOOSTER PUMP INSTRUCTION MANUAL **V-SERIES**



V760AH

ASIA AUTOMATIC PUMP CO.,LTD http://www.evergushpump.com.tw

OPERATION



- 1. Make sure of using the right voltage.
- 2. Remove the priming cap and pour water into the pump and suction piping, then secure the plug.
- 3. Insert a screw driver cross into the shaft slot, and turns the shaft 2-3 rounds to check if the pump runs normally, then open one faucet on the delivery side, then turn the power switch ON.(FIG.1)
- 4. After the power switch on, the motor should turn immediately. After a few seconds, the water should be delivered.
- 5. If the water does not be delivered immediately, turn the power OFF. Repeat step 2 and set power ON/OFF continuously to make the suction piping be filled with water.
- 6. Once the water is pumped out, close the faucets on the delivery side to check the automatic stopping and pumping operation

IMPORTANT NOTES

- 1. Use the right voltage and wiring by the connecting diagram. Motor must be grounded in compliance with applicable electrical code to avoid accident.
- 2. Please use a sturdy foundation and bolt the pump to it securely.
- 3.Be sure to arrange earthling or circuit breaker against electric leakage.
- 4. The pump should be supplied through a residual current device(RCD)having a rated residual operating current not exceeding 15mA.
- 5. The pump should be installed as close as to the reservoir or well avoid the low efficiency due to the long suction pipe.

- 6. The location must be dry with good ventilation and adequate space.
- 7. Do not run without water actually pumping. Do not operate hot water (more than 55°C), or the other liquid except normal water.
- 8.Be careful not to allow the foreign matter(chips,dirt,sand,glue,etc) into the pump, or they will damage and shorten the life of pump.
- 9. Piping joints should be fitted carefully to prevent leakage.
- A. Leakage in the suction piping will cause the pump does not function well.
- B. Leakage in the discharge piping will cause a high frequency ON /OFF motor operation while all the faucet and valves are closed.
- 10. Keep the faucets opened fully to get more efficient operation. Never keep continuous operation under the condition of half open.
- 11. If the supply cord is damaged, it must be replaced by a special cord or assembly available from the manufacturer or its service agent.

TROUBLESHOOTING

(Turn the power switch OFF before fixing.)

1.MOTOR FAILS TO START OR **RESTART AFTER A SHORT-TERM** RUNNING

The overheating protector is mounted directly on the motor windings. It will stop the motor automatically when the motor temperature is up to abnormal, and restart the motor after the temperature back to normal in 20 Minutes.

- A. Check the electrical power source, fuse, and circuit breaker.
- B. Check if pump is locked by rust or foreign objects.
- C. Check if the ventilation of the location is bad for causing the overheating of motor.
- D. Check if thermal overload protector is disconnected or breakdown. If it's failure , it must be replaced by service agent.

Warning: Don't open the cover or touch thermal protector at random unless turn off power by technicians.(PIC.1)

PIC.1

2.PUMP CYCLES FREQUENTLY WHILE ALL THE FAUCETS AND **VALVES ARE CLOSED:**

- a. Check and fix the leakage in discharge piping, faucets, and valves.
- b.Clean pump check valve which may be locked by foreign objects.


3.PRESSURE SWITCH FAILS TO **FUNCTION**

The pump's pressure switch has been set accurately. Please do not try to adjust except by qualified personnel.

- a. If the motor does not start after any of the faucets or valves are opened, adjust the pressure setting screw to the "+" direction (counterclock-wise)until the motor Starts.(FIG.2)
- b. If the motor fails to stop after all the faucets and valves are closed. adjuts the pressure setting screw to the "-"direction(clockwise)until the motor stops.(FIG.2)
- c.Repeat step(a)and (b)until the pump works normally.

APPLICATIONS:

- 1. Directly and automatically supply water to the building without roof water tower.
- 2. Automatically increase pressure as soon as the insufficient water pressure occurs in the top floor.
- 3. To be used on supplying water for washing machine and heater if water pressure is too low.
- 4. To drain accumulated water for civil and architecture engineering, to be applicable to the skyscraper villa, pond and farm.
- 5. To be used on circulating water for garden and on supplying water for auto car-washer.



SPECIFICATION:

V460ASH -Equipped with thermal overload protector -Stainless Steel Pump -Aluminum motor shell -Model Number -Auto Booster Pump Model

| | | | 1 | | | |
|---------------------------------|------------------|------------------|------------------|--------|--------------|------|
| Model No: | V260AH;V260ASH | | V460AH;V460ASH | | V760AH | |
| Output(HP) | 1/4 | 1/4 | 1/2 | 1/2 | 1 | 1 |
| Cycle(Hz) | 50 | 60 | 50 | 60 | 50 | 60 |
| R.P.M. | 2900 | 3500 | 2900 | 3500 | 2900 | 3500 |
| Rated head(m) | 12 | 16 | 16 | 20 | 20 | 28 |
| Rated flow(L/min) | 20 | 20 | 25 | 25 | 30 | 32 |
| Max. head(m) | 27 | 33 | 35 | 43 | 38 | 45 |
| Max. flow(L/min) | 32 | 35 | 40 | 45 | 60 | 70 |
| Pressure switch ON(kg/cm²) | 1.0 | 1.4 | 1.4 | 2.0 | 2.0 | 2.0 |
| OFF(kg/cm²) | 2.0 | 2.4 | 2.4 | 3.2 | 3.2 | 3.2 |
| Inlet mm(inch) 20(3/4"), 25(1") | | 20(3/4"), 25(1") | | 25(1") | | |
| Outlet mm(inch) | 20(3/4"), 25(1") | | 20(3/4"), 25(1") | | 25(1") | |
| Package size (cm) | 30X23.5X46 | | 30X23.5X46 | | 33X27.5X49.5 | |
| Gross weight (kg) | 10.7 | 10.7 | 12 | 12 | 22 | 22 |

● V260ASH, V460ASH- Stainless Steel Pump

Suction Lift: Max.6M